## **Electromechanical Rotary Latches**

## Selection guide

	Latch Series	Latch Type	Load Rating	Sealed Electronics	Installation	Material	Integrated Microprocessor-Based Control	Integrated Card Reader or Keypad	Nominal Voltage Range
ES	R4-EM-9	Rotary Push-to-Close	Medium		Concealed	Steel and Plastic	~		12-24 VDC
TARY LATCHI	R4-EM-8	Rotary Push-to-Close	Medium		Concealed	Steel and Plastic			12 or 24 VDC
HANICAL RO' PAGES 23-37	R4-EM-5 & 7	Rotary Push-to-Close	High	<b>/</b>	Concealed	Steel or Stainless Steel	<b>/</b>		12-24 VDC
ELECTROMECHANICAL ROTARY LATCHES Pages 23-37	R4-EM-4 & 6	Rotary Push-to-Close	Medium		Concealed	Plastic	~		12-24 VDC
	R4-EM-1 & 2	Rotary Push-to-Close	High		Concealed	Steel	~		12-24 VDC

# **Electromechanical Rotary**

Pages 23 - 37



The R4-EM series delivers the convenience of electronic access control with the security of a proven, robust, rotary latch design in a compact, integrated package. Easy push-to-close operation and electronic actuation simplify access across a wide variety of applications. An optional microswitch provides feedback on latch status, and a full range of manual release options are available.

- **⇒** 12-24 VDC operation, minimal current consumption
- Accepts control inputs from any access control device
- Operates against heavy mechanical loads
- Corrosion-resistant version available for outdoor use
- Optional door sensor















## **Electromechanical Rotary Latches**

**Overview** 







#### R4-EM-9 Series — Full-featured

The microprocessor controlled R4-EM 9 Series delivers next generation electronic rotary latching. All inputs are routed through the internal microprocessor, allowing expanded programing capability and customization of latch functionality. Extended housing provides added protection of the cam and an integrated trigger sensor provides indisputable lock/unlock status reporting. Additionally, the 9 Series offers a door retention feature which allows a door or panel to remain in the closed position until it is ready to be opened.

## R4-EM-8 Series — Basic functionality

The R4-EM 8 Series combines the efficient and robust performance of a rotary latch mechanism with simplified DC motor actuation. The R4-EM 8 Series is available with or without an extended housing option to accommodate door sensing and to provide added protection of the locking cam. Additionally, the 8 Series is available with an integrated connector and mechanical override bracket, and features simple,

concealed two-hole installation.

**R4-EM-8** 

R4-EM-5 & 7

#### R4-EM 5 & 7 Series — Outdoor use

The R4-EM Outdoor provides reliable electronic access control in demanding environments. With its corrosion-resistant plated-steel or stainless steel outer body construction and fully-sealed internal actuator, the R4-EM Outdoor provides reliable electronic locking that is resistant to moisture and dust. The embedded electronic control allows integration with an external control system and flexible, concealed installation accommodates a variety of outdoor applications.

R4-EM-4 & 6

## R4-EM 4 & 6 Series — Compact & lightweight

The R4-EM Light Duty delivers proven electronic access control in a compact, lightweight integrated package. Easy push-to-close operation and simple installation make it an ideal solution for transitioning from mechanical to electronic access. The R4-EM Light Duty is available in both auto re-lock and delayed re-lock versions for added flexibility. Multiple mounting configurations and a compact size afford easy integration into existing designs.



R4-EM-1 & 2


### R4-EM 1 & 2 Series — All-metal construction

The original, all-metal construction R4-EM delivers the convenience of electronic access control with the security of a proven, robust, all-metal rotary latch. Easy push-to-close operation and electronic actuation simplify access across a wide variety of applications. The R4-EM series accepts access control signals from access control devices as well as networked systems. An optional internal microswitch provides an output signal to remotely monitor latch status or control external systems.

- Push-to-close, electronic release
- High electromechanical release load
- Minimal power draw
- Optional door sensor
- Mechanical over-ride
- 12V and 24V options



Latch and door status indication



access control override





## R4-EM 9 Series Electromechanical Rotary Lock

Concealed cam

Electronic access with internal motor control

6

**12V** 


**24V** 

- Push-to-close, electronic release
- High electromechanical release load
- Minimal power draw
- Integrated connector
- Extended housing for added security
- Door and Trigger Sensor
- Microswitch to detect latch status
- Mechanical over-ride with integrated cable bracket
- 12V to 24V operations
- Efficient DC gear motor actuation
- Detent mechanism for pull-open function
- Simple two-hole installation




Other options available. For complete details on variety, part numbers, installation and specification, go to

www.southco.com/R4-EM



#### **Part Number Selection**






**24V** 

#### Installation

**Panel Preparation** 

Base Mounting Style	Recommended minimum mounting hole		
1/4-20 thread	Ø 7.2 (.283)		
M6 thread	Ø 6.9 (.272)		
Thru hole	Ø 7.6 (.300)		



#### **Operation**

See page 34 for operating instructions

#### **Accessories**

#### Striker Bolt or Cast Striker

See page 35







## **Electronic Actuators** See page 42















Wiring/Junctions



Dimensions in millimeters (inch) unless otherwise stated

#### **Material & Finish**

Top Housing: PC/ABS or Aluminum Bottom Housing: PC/ABS or Zinc,

Die Cast

Pivot Pins: Steel, zinc plated Cam, Trigger: Steel, sealed

Springs: Stainless steel passivated Trigger Interlock Lever: Glass-filled nylon

Bistable Spring Retainer: Zinc Alloy Drive Cam: Acetal, black

Output Cam: Acetal, white

#### **Electrical Specifications**

Recommended Operating Voltage:

12 to 24 VDC

Typical Operating Current:

12 V Models: Less than 500mA

#### **Latch Connector Pin Assignment**

PIN 1: Ground (-)

PIN 2: Power (+)

PIN 3: Control Signal

PIN 4: Latch Status

PIN 5: None

PIN 6: Door status

Other options available. For complete details on variety, part numbers, installation and specification, go to





## R4-EM 8 Series Electromechanical Rotary Lock

Door sensor option · Extended housing option Electronic access without internal motor control


## 6

19V

IZV

**24V** 


- Push-to-close, electronic release
- Auto relock functionality
- Minimal power draw
- Integrated connector
- Extended housing option for added security
- Optional door sensor
- Microswitch to detect latch status
- Mechanical over-ride with integrated cable bracket
- Efficient DC motor actuation
- Simple two-hole installation




Other options available. For complete details on variety, part numbers, installation and specification, go to

www.southco.com/R4-EM

#### **Extended Housing**



#### **Part Number Selection**





**24V** 

#### Installation Striker center line $15.6 \pm 1.2 (.614 \pm .046)$ Extended 28 **Panel Preparation** housing (1.10) Panel cutout center line version $15.6 \pm 0.5 (.614 \pm .020)$ Recommended **Base Mounting** minimum 14 (.55) Minimum Style mounting hole Striker center line $2.5 \pm 0.1 (.098 \pm .004)$ 15 1/4-20 thread Ø 7.2 (.283) 5 (.197) Minimum (.59)M6 thread Ø 6.9 (.272) Ø 7.6 (.300) Thru hole $42.5 \pm 0.2$ (1.673 ±.008) Mounting holes (see table) **Operation** See page 34 for operating instructions - 18 ±0.2 → $(.709 \pm .008)$

#### **Accessories**

#### Striker Bolt or Cast Striker

See page 35







#### **Material & Finish** Top housing: Nylon

Gearbox cover: PC/ABS Bottom housing, Pivot pins, Screws: Steel, zinc plated

Cam, Trigger: Steel, sealed

Gears: Acetal

Pin, Springs: Stainless steel

**Electrical Specifications** 

Recommended Operating Voltage:

12 V Models: 8 to 14 VDC 24 V Models: 21 to 26 VDC Typical Operating Current: 12 V Models: Less than 200mA 24 V Models: Less than 100mA Latch status switch: 1A Maximum

### **Latch Connector Pin Assignment**

PIN 1: Power

PIN 2: Ground (-)

PIN 3: None

PIN 4: Latch status signal





## R4-EM 5 & 7 Series Electronic Rotary Latch


Sealed motor · Stainless steel housing option Electronic access with internal motor control




**12V** 

**24V** 

- Motor actuator sealed against water and dust ingress to IP56
- Corrosion resistant platedsteel and stainless steel options
- Push-to-close, electronic release
- Versatile rotary mechanism
- Concealed latching
- Microprocessor control
- Auto or delayed relock functionality
- Minimal power draw
- Optional internal microswitch for latch status
- Simple mechanical over-ride



Other options available. For complete details on variety, part numbers, installation and specification, go to




**24V** 

#### Installation

**Panel Preparation** 

Base Mounting Style	Recommended minimum mounting hole		
1/4-20 thread	Ø 7.2 (.283)		
M6 thread	Ø 6.9 (.272)		
Thru hole	Ø 7.6 (.300)		



**Accessories** 

Operation

Striker Bolt or Cast Striker

See page 34 for operating instructions

See page 35



Cable Mounting Kit

See page 35





Southco®

Dimensions in millimeters (inch) unless otherwise stated

#### **Material & Finish**

Mechanism

Housing, Cam, Trigger, Pins: Zinc nickel plated steel or stainless steel Springs: 300 Series stainless steel

Electronic Actuator Housing: PC/ABS

Bellows, Wire seal: Silicone Perimeter Seal: Buna

Cams: Acetal Grommet: TPE

#### **Electrical Specifications**

Recommended Operating Voltage: 12 to 24 Volt DC

Typical Operating Current (average at no load): Less then 600mA at 12 VDC

Input Signal Current Draw: 25mA

Maximum at 24 VDC

Micro-switch Rating: 3A Maximum

at 12VDC

# Wire Color Code / Connector Pin Assignment:

PIN 1: Brown: Ground (-)

PIN 2: Red: Power 12 to 24 Volts DC

PIN 3: Orange: Control Signal

12 to 24 Volts DC

PIN 4: Black: Microswitch Common

PIN 5: Blue: Microswitch N.O.

Contact

PIN 6: Grey: Microswitch N.C.

Contact

Other options available. For complete details on variety, part numbers, installation and specification, go to



# South Comment of the Comment of the

## R4-EM 4 & 6 Series Electronic Rotary Latch


Compact size · Lightweight
Electronic access with internal motor control

<del>[-</del>


12V

24V

- Light weight construction
- Auto re-lock and delayed re-lock version
- Push-to-close, electronic release
- Versatile rotary mechanism
- Concealed latching
- Microprocessor control
- Minimal power draw
- Simple mechanical over-ride
- Optional internal microswitch for latch open/close output signal



Other options available. For complete details on variety, part numbers, installation and specification, go to






**24V** 

#### Installation

**Panel Preparation** 

Base Mounting Style	Recommended minimum mounting hole		
10-24 thread	Ø 5.6 (.220)		
M5 thread	Ø 5.9 (.232)		
Thru hole	Ø 6.1 (.240)		

See page 34 for operating instructions



Accessories

**Operation** 

Striker Bolt

See page 35



**Cable Mounting Kit** See page 35







Dimensions in millimeters (inch) unless otherwise stated

#### **Material & Finish**

Housings: PC/ABS Cam: Glass-filled nylon

Trigger: PBT

Springs: Stainless Steel

Pins: Steel, zinc plated

#### **Electrical Specifications**

Recommended Operating Voltage: 12 to 24 VDC

Typical Operating Current (average at no load): Less than 600mA at 12VDC

Input Signal Current Draw: 25mA Maximum

\*\*Optional microswitch closes upon latch closure Microswitch Rating: 3A Max at 12 VDC

# Wire Color Code / Connector Pin Assignment:

PIN 1: Brown: Ground (-)

PIN 2: Red: Power 8 to 26 Volts DC

PIN 3: Orange: Control Signal

8 to 26 Volts DC

PIN 4: Black: Microswitch Common

PIN 5: Blue: Microswitch N.O.

Contact

PIN 6: Grey: Microswitch N.C.

Contact

Other options available. For complete details on variety, part numbers, installation and specification, go to





## R4-EM 1 & 2 Series Electronic Rotary Latch


All-metal construction
Electronic access with internal motor control



12V


**24V** 

- High strength, steel construction
- Operates against high mechanical loads
- Push-to-close, electronic release
- Versatile rotary mechanism
- Concealed latching
- Microprocessor control
- · Minimal power draw
- Simple mechanical override
- Optional internal microswitch for latch open/close output signal



Other options available. For complete details on variety, part numbers, installation and specification, go to


www.southco.com/R4-EM



# Latch Wiring Connections With connector Molex Microfit 3.0 series PIN 6 PIN 5 PIN 2 PIN 2 PIN 2 PIN 2 PIN 2

PIN 1 Indicator

#### **Part Number Selection**



None Standard configuration

- 2 Strong (kick out) cam spring (delayed relock)
- 3 High strength cam
- 4 High strength cam with strong (kick out) cam spring (delayed relock)

Dimensions in millimeters (inch) unless otherwise stated




**24V** 

#### Installation

**Panel Preparation** 

Base Mounting Style	Recommended minimum mounting hole		
1/4-20 thread	Ø 7.2 (.283)		
M6 thread	Ø 6.9 (.272)		
Thru hole	Ø 7.6 (.300)		



**Accessories** 

Operation

Striker Bolt or Cast Striker

See page 34 for operating instructions

See page 35











Dimensions in millimeters (inch) unless otherwise stated

#### **Material & Finish**

Mechanism

Housing: Steel, zinc plated Cam, trigger: Steel, zinc plated Springs: 300 Series stainless steel

Pins: Steel, zinc plated

Electronic Actuator: Housing: PC/ABS Cam / follower: Acetal

#### **Electrical Specifications**

Recommended Operating Voltage: 12 to 24 Volt DC
Typical Operating Current: Less than 500mA at 12 VDC
Peak/Stall Operating Current: 1 A
Standby Current: 185uA
Input Signal Current Draw: 25mA
\*\*Optional microswitch closes upon latch closure
Microswitch Rating: 3A at
12VDC Maximum

## Wire Color Code / Connector Pin Assignment:

PIN 1: Brown: Ground (-)

PIN 2: Red: Power 8 to 26 Volts DC

PIN 3: Orange: Control Signal

8 to 26 Volts DC

PIN 4: Black: Microswitch Common

PIN 5: Blue: Microswitch N.O.

Contact

PIN 6: Grey: Microswitch N.C.

Contact

Other options available. For complete details on variety, part numbers, installation and specification, go to







## **R4-EM** Electronic Rotary Latch

## Operating instructions

#### **Operation** - Auto relock


- 1. The signal unlocks the R4-EM latch and releases the spring loaded cam which rotates out to push a lightweight door open. The mechanism will cycle through unlatched then relatched state automatically, regardless of input signal on time.
- 2. Push door closed to engage striker after unlock time has expired. Striker will rotate cam to closed position.





#### **Operation -** Delayed relock

- The signal unlocks the R4-EM latch leaving a biased closed door in the closed position.
   The unlock time is controlled by the access control device.
- Manually pull door/striker free from R4-EM latch.
- 3. Manually push door closed.
  Striker will rotate cam to closed position, however latch will remain unlocked and can be re-opened as long as signal is present.
- After accessing the door, the signal can be removed to re-lock the R4-EM. This can be done with the door in the open or closed position.



lock R4-EM Latch





## **R4-EM** Electronic Rotary Latch

## Strikers - Cable mounting kits



**Material and Finish** 

Cast strikers: Zinc alloy

\*Note: Latch and striker

the latch trade drawing at

www.southco.com.

stainless steel

nylon, black


Striker bolts: Steel, zinc plated or

Cable mounting kits: Glass-filled


installation details can be found on




Part number R4-90-121-10




# **Striker Bolt - Small**Part number R4-90-511-20



Cast Striker with Door Sensor Part number R4-90-804-10\*
Cast Striker without Door Sensor Part number R4-90-800-10\*






#### **Cable Mounting Kit**

Part number R4-EM-52 — Rivets included Part number R4-EM-72 — Screws included



Part number R4-EM-87 — Rivets included

Part number R4-EM-952



	Strike	er Bolt	Cast S	Striker		Cable Mo	unting Kit	
	R4-90-121-XX	R4-90-511-20	R4-90-800-10	R4-90-804-10	R4-EM-52	R4-EM-72	R4-EM-87	R4-EM-952
R4-EM-9	~		<b>V</b>	<b>/</b>				<b>/</b>
R4-EM-8	~		V	~				
R4-EM-5 & 7	~		~		~		/	
R4-EM-4 & 6		~				~		
R4-EM-1 & 2	~		~		~		~	







## **R4-EM** Mechanical Override System

- Adapts to any standard Southco R4-EM Electronic Rotary Latch
- Choose from flat key or tubular key cam latch for remote key lock
- Simple installation with multiple adjustments and customized cable lengths to suit any application.
- Accommodates clockwise or counter clockwise key rotation for latch release

Southco now offers a standard solution for remote mechanical actuation of the R4-EM Electronic Rotary Latch. The cable based solution provides a simple means of mechanically releasing the electronic lock in the event of electrical power loss providing fully redundant access.

#### Installation









#### **How to Order**

Step 1 Select mechanical override lock and corresponding AC actuator assembly and AC cable bracket

	Description	Part Number	
	A5 Actuator	A5-99-136	
		AND	
E5 Latch	AC Cable Bracket (Clockwise Rotation to Unlatch)	AC-0-49617-11-R	
Push-to-Close assembly See page 128		OR	
See drawing J-E5-53-A	AC Cable Bracket (Counter Clockwise Rotation to Unlatch)	AC-0-49617-11-L	

	Description	Part Number				
	A5 Actuator	A5-99-157				
		AND				
PT Latch	AC Cable Bracket (Clockwise Rotation to Unlatch)	AC-0-49618-11-R				
Tubular Key cam Lock See page 170		OR				
See drawing J-PT-1	AC Cable Bracket (Counter Clockwise Rotation to Unlatch)	AC-0-49618-11-L				

#### Step 2 Determine mechanical cable length required

Mechanical Cable See drawing J-AC-C	AC-COHO-4-LLLL-TTT	LLLL - Length from behind ball end to end of cable TTT - Raw cable extension portion of LLLL length	
--	--------------------	--	--

**Step 3** Order cable mounting kit (one per R4-EM latch). See page 35 to select the kit to match your application.

R4-EM-52	R4-EM-72	R4-EM-87	R4-EM-952	



